



Poly VideoOS Software

Poly G7500, Poly Studio X50, and Poly Studio X30

Poly announces the release of Poly VideoOS software 3.2.0. The Poly VideoOS software build contains the following device software versions:

- Poly TC8 3.2.0
- Poly Microphone IP Adapter 3.0.0
- Poly IP Table Microphone 3.0.0
- Poly EagleEye Cube USB Camera 1.3.0

Contents

What’s New	1
Security Updates	5
Installation	5
Version History	5
Language Support	7
Resolved Issues	8
Known Issues	9
System Constraints and Limitations	12
Interoperability	16
Get Help	20
Copyright and Trademark Information	21

What’s New

These release notes provide information on updates, features, and resolved and known issues for systems using Poly VideoOS software with Poly G7500, Poly Studio X50, and Poly Studio X30.

3.2.0 includes the following features:

- [Support for Zoom Rooms 5.1.2](#)

-
- [Native Interoperability with StarLeaf](#)
 - [Native Interoperability with RingCentral Rooms](#)
 - [Multicamera Support](#)
 - [USB Camera Support](#)
 - [Limit Maximum Camera Digital Zoom](#)
 - [Reset Camera Settings to Defaults](#)
 - [Configuring HDMI Input as a People Source](#)
 - [3.5 mm Audio Output on Studio X50](#)
 - [TC8 Web Proxy Enhancements](#)
 - [Updating TC8 Software Using a USB Flash Drive](#)
 - [Automatic Software Updates](#)
 - [Default Logging Level](#)
 - [Provisioning Your System with Poly Lens](#)
 - [Device Mode Provisioning Parameter](#)

Support for Zoom Rooms 5.1.2

Poly VideoOS software 3.2.0 supports version 5.1.2 of the Zoom Rooms and Zoom Rooms Controller applications for G7500, Studio X50, and Studio X30 systems.

Native Interoperability with StarLeaf

Poly extends the interoperability of G7500, Studio X50, and Studio X30 systems to work with StarLeaf. With Poly Zero Touch Onboarding (ZTO), you can place and join StarLeaf calls as soon as your system powers on.

Note: You can use StarLeaf only in single-monitor setups.

Native Interoperability with RingCentral Rooms

Poly extends the interoperability of Studio X50 and Studio X30 systems to work with RingCentral Rooms (RCV Rooms). The RCV Rooms software is currently a beta release. With Poly Zero Touch Onboarding (ZTO), you can place and join RCV Rooms calls as soon as your system powers on.

Note: You can use RCV Rooms only in single-monitor setups.

Multicamera Support

Poly Video Mode on G7500 and Studio X50 systems support multiple attached cameras. When you attach a camera to your G7500 or Studio X50 system, you can select the active near-end camera in or out of a call.

You can connect a maximum of five cameras to your G7500 system and a maximum of three cameras to your Studio X50 system.

USB Camera Support

You can connect a supported USB camera to your G7500 or Studio X50 system to use as a primary or secondary camera.

Poly supports the following USB cameras with this release:

- Poly EagleEye Cube USB camera
- Poly Studio USB video bar
- Polycom EagleEye IV USB camera
- Polycom EagleEye Mini USB camera

Using the Poly Studio USB Video Bar Microphone and Speakers

With your system, you can use the Poly Studio USB video bar as a microphone and speakers if you don't connect other microphones or speakers to the system.

Note the following when using the Poly Studio USB video bar:

- You must enable USB audio in the G7500 or Studio X50 system web interface to use the Poly Studio USB video bar microphone and speakers.
- Using the Poly Studio USB video bar microphone and speakers with a Studio X50 system disables the Studio X50 built-in microphones and speakers.

Limit Maximum Camera Digital Zoom

By default, Studio X50 and Studio X30 systems limit the maximum camera digital zoom to 3x. This prevents your camera from going beyond digital zoom limits that may reduce video quality. Configure this setting in the system web interface.

Reset Camera Settings to Defaults

After changing camera settings, you can quickly reset all camera settings to the default configuration in the system web interface.

Configuring HDMI Input as a People Source

You can configure the **HDMI Input** as a people source in Poly Video Mode. You can configure the HDMI input in or out of a call. This feature isn't available on Studio X30 systems.

Configuring the HDMI input as a people source lets you take full advantage of the available transmit bandwidth to increase the video quality of the HDMI input. When using the HDMI input as a people source, you lose the annotation tools normally available to you in a content sharing session.

3.5 mm Audio Output on Studio X50

You can now configure the Studio X50 to use its 3.5 mm audio port for audio output.

TC8 Web Proxy Enhancements

TC8 devices can communicate with an external cloud service from behind a web proxy. No extra setup is required; the device uses the web proxy information configured on your paired video system.

TC8 devices communicate through a web proxy if the paired video system downloads the required proxy-auto configuration (PAC) file using the web proxy auto-discovery protocol (WPAD). They can also use the Digest NTLM authentication methods that the paired system uses.

Updating TC8 Software with a USB Flash Drive

You can update a connected TC8 device using a USB flash drive connected to your video system.

Automatic Software Updates

Automatic software updates are now enabled by default for all conferencing applications except Microsoft Teams and Zoom. By default, your system automatically updates between 1:00 a.m. and 5:00 a.m.

Default Logging Level

In Poly VideoOS software 3.2.0, the default logging level is now set to **Critical**. Poly doesn't recommend setting the log level to **Debug** for long durations (weeks and months). If you set the log level to **Debug**, **Info**, or **Warning**, Poly recommends that you enable automatic transfer of logs to a USB flash drive or enable remote logging.

Provisioning Your System with Poly Lens

You can provision your system using Poly Lens. Configure your system to use Poly Cloud as the provisioning server type on your system and complete provisioning using the associated Poly Lens account.

See the [Poly Lens](#) help documentation for information on configuring the server for provisioning.

Device Mode Provisioning Parameter

You can enable or disable Device Mode using the following provisioning parameter:

device.local.deviceMode.enable

Enables device mode on your system.

True (default)

False

Security Updates

See the [Polycom Security Center](#) for information about known and resolved security vulnerabilities.

Installation

Get the latest version of Poly VideoOS at the [Poly Online Support Center](#). You don't need a software version key to install version 3.2.0.

You can install updates a few different ways. See your system's [Poly Video Mode Administrator Guide](#) or [Poly Partner Mode Administrator Guide](#) for more information.

Some notes on software updates:

- If you use Zoom Rooms as your primary conferencing application, Poly recommends regularly updating your system in the Zoom Admin Portal.
- If your system uses a TC8 device, Poly strongly recommends updating your system to the latest release.

Downgrading Software

Poly recommends the following if you want to downgrade from version 3.2.0:

- If your system is managed by the Poly Zero Touch Onboarding (ZTO) service, don't downgrade. Contact your authorized Poly dealer for information.

See your system's [Poly Video Mode Administrator Guide](#) or [Poly Partner Mode Administrator Guide](#) for more information on how to downgrade.

Version History

This following table lists the release history of the G7500, Studio X50, and Studio X30 systems.

Release History

Release	Release Date	Features
3.2.0	August 2020	<ul style="list-style-type: none"> • Support for Zoom Rooms 5.1.0 • Native Interoperability with StarLeaf • Native Interoperability with RingCentral Rooms • Multicamera Support • USB Camera Support • Limit Maximum Camera Digital Zoom • Reset Camera Settings to Defaults • Configuring HDMI Input as a People Source • 3.5 mm Audio Output on Studio X50 • TC8 Web Proxy Enhancements • Updating TC8 Software Using a USB Flash Drive • Automatic Software Updates • Default Logging Level • Provisioning Your System with Poly Lens • Device Mode Provisioning Parameter
3.1.3	July 2020	<ul style="list-style-type: none"> • Camera enhancements
3.1.1-216125	June 2020	<ul style="list-style-type: none"> • Support for Zoom Rooms 5.0.2
3.1.1-216122	June 2020	<ul style="list-style-type: none"> • Fixes to audio issues and conference provider switching
3.1.1-216109	June 2020	<ul style="list-style-type: none"> • Studio X Family Certified Collaboration Bar for Microsoft Teams • Native Interoperability with 8x8 • Adjust Studio X50 or Studio X30 Camera Lighting Based on Workspace • Disable Poly Device Mode • System Acceptlist

3.1.0	May 2020	<ul style="list-style-type: none"> • Support for Zoom Rooms 5.0 • Native Interoperability with GoToRoom by LogMeIn • Pairing a Poly Trio System • Using the System as a Camera and Audio Peripheral • New Camera Tracking Option for Studio X Family • IPv6 Support • Security Banner • New Security Defaults • PKI Certificates for Poly TC8 • 802.1X for TC8 • System Audio Enhancements • Poly Lens Enhancements • Improving Picture Quality • Out of Office Sleep Settings
3.0.2	February 2020	<ul style="list-style-type: none"> • Fixes to audio issues during calls using Zoom Rooms
3.0.1	February 2020	<ul style="list-style-type: none"> • Poly Lens support • Studio X50 and Studio X30 camera enhancements • Studio X50 and Studio X30 audio enhancements • Using a TC8 behind a web proxy
3.0.0	December 2019	<ul style="list-style-type: none"> • Introducing the Poly Studio X50 and Poly Studio X30 systems • Introducing Poly Partner Mode • Poly interoperability with Zoom Rooms • Introducing the Poly TC8 device • Poly NoiseBlockAI • Documentation updates
2.1.0	August 2019	<ul style="list-style-type: none"> • Poly EagleEye Cube USB camera support • Persistent HDMI content • Comprehensive provisioning template • CEC support • H.460 on by default • Ability to configure wireless channels for Miracast-certified devices • Important sleep/wake fixes • UI updates
2.0.0	May 2019	<ul style="list-style-type: none"> • Introducing the Poly G7500 system

Language Support

G7500, Studio X50, and Studio X30 systems support the following languages in Poly Video Mode:

- Arabic

- Chinese (Simplified)
- Chinese (Traditional)
- British English
- American English
- French
- German
- Hungarian
- Italian
- Japanese
- Korean
- Norwegian
- Polish
- Portuguese (Brazilian)
- Russian
- Spanish

In Partner Mode, your conferencing provider may have a different set of supported languages.

Resolved Issues

The following table lists the resolved issues in this release.

Resolved Issues

Category	Issue ID	Description
Audio	EN-166415	Dialing out with RMX Manager to two video systems using M-Mode and mono audio results in SIP calls with poor audio quality.
Calling	EN-154858	You can place a Zoom call on a paired TC8 device while the video system's software is still updating, but the call disconnects once the update completes.
Calling	EN-174602	The TC8 device can't save camera presets for the far-site camera in a call.
Call Management	EN-175808	Studio X50 systems registered to a Polycom RealPresence DMA system fail to receive incoming SIP calls after being idle overnight.
Content	EN-160065	The screen mirroring options remain live in the system web interface even though someone is sharing content. Modifying the settings while sharing content can cause problems. For example, if you disable AirPlay while someone's sharing content from their AirPlay-certified device, the content drops.
Device Management	EN-140507	When the G7500 system is sleeping, EagleEye Cube USB camera information doesn't display in the system web interface.

Hardware	EN-136674	On your G7500 system, unplugging a Poly IP Table Microphone from the first link-local network (LLN) port and plugging it back in causes any other connected table microphones to stop working.
Hardware	EN-140535	Rapidly disconnecting and reconnecting an EagleEye Cube USB camera may cause the system to crash.
Hardware	EN-165611	After initial system setup with a connected EagleEye Cube USB camera, the local video doesn't display correctly.
Hardware	EN-173607	If you connect a USB monitor with a built-in webcam, your video preview doesn't display and the Input Format in the system web interface displays USB .
Installation	EN-164564	During system setup, a Studio X50 or Studio X30 system may take up to 4 minutes to find and pair with a TC8 device purchased at the same time. Once paired, you can select a conferencing application (Poly Video Mode or Partner Mode).
Network	EN-143744	If your system's VLAN changes, your connected IP microphones show as Disconnected .
Network	EN-175519	The system can't reconnect to the network and fails on startup after connecting LAN cables in network environments where the DHCP lease time is set to Forever .
Peripherals	EN-172144	Poly TC8 doesn't display under the Available Devices list in the system web interface and the TC8 local device interface displays a <code>Waiting for Pairing</code> message.
Software Update	EN-168821	You can't update software with a USB flash drive when the system is in Partner Mode.
User Interface	EN-154200	When in Poly Partner Mode, the G7500, Studio X50, and Studio X30 system web interface Home Screen settings don't work.
User Interface	EN-155417	Changing the Time Server setting in the system web interface from Auto to Off and back to Auto causes the time to desync between your system and the TC8 device.
User Interface	EN-176429	If you set the second Configure Monitor setting to Off on a G7500 or Studio X50 system running Teams, the system changes the first monitor output to 4K and the user interface doesn't display properly.

Known Issues

The following table lists known issues in this release.

Note: These release notes don't provide a complete listing of all known issues that are included in the software. Issues not expected to significantly impact customers with standard voice and video conferencing environments may not be included. In addition, the information in these release notes is provided as-is at the time of release and is subject to change without notice.

Known Issues

Category	Issue ID	Description	Workaround
Audio	EN-119155	Downloading logs during a call temporarily disconnects the Poly Microphone IP Adapter, resulting in a loss of audio on the far end.	When using a microphone adapter, don't download logs during a call.
Audio	EN-173373	You can't see the audio meter for paired Poly Trio microphones in the system web interface. This can occur after upgrading your system from 3.0.2 to 3.1.0. (You can see the Poly Trio audio meter on the local interface.)	Reset the system and pair the Poly Trio.
Audio	EN-177041	In calls processed by RealPresence Collaboration Server 1800, you can hear a ticking sound on a G7500 or Studio X50 system when you enable M-Mode and stereo.	Disable one of the following settings on your system: <ul style="list-style-type: none"> • Enable M-Mode • Polycom StereoSurround
Audio	EN-184268	When using a Trio C60 as an audio device in Poly Video Mode, the audio distorts when using Device Mode for an extended period of time.	Stop and restart Device Mode.
Calling	EN-184614	If you enable the Auto Answer Point-to-Point Call setting, the system automatically answers incoming calls (with audio) that come in while you're already in a call.	Configure the Auto Answer Point-to-Point Call setting to Do Not Disturb or No .
Content	EN-156868	In content shared through an HDMI connection, black text on a red background is blurry.	None.
Content	EN-173263	If you set the Orientation on a Studio X30 system to Inverted and keep an HDMI source always connected to share content, the near video may display upside down after you stop sharing HDMI content.	Do one of the following: <ul style="list-style-type: none"> • Disconnect the HDMI source. • Stop and restart your camera.
Device Management	EN-145107	You can create a name for your EagleEye Cube USB camera in the Polycom Companion application that's up to 60 characters long, but the G7500 system web interface cuts off the name after 32 characters.	Use a camera name that isn't longer than 32 characters.
Directories	EN-144594	When uploading contacts from an XML file, the system doesn't display more than one contact with the same name even if the <code>uniqueid</code> attribute is different.	Create contacts with unique names.
Hardware	EN-145997	Swapping a 4K monitor for a 1080p monitor while your system is asleep results in losing the monitor signal.	Restart the system.

Network	EN-182303	When your conferencing provider is set to Partner Mode, the system enables wireless connectivity. You can't disable the Enable Wireless Connectivity setting in the system web interface.	To disable this setting you set the device.wifi.enable configuration setting via Poly Lens or RealPresence Resource Manager.
Peripherals	EN-154642	Recent call history still displays on the TC8 device after you clear recent calls in the paired video system web interface.	Unpair then pair the TC8 device to clear the recent call list.
Peripherals	EN-178323	Entering Device Mode unregisters the gatekeeper and SIP registrar server on Poly Studio X30.	Exit Device Mode.
Peripherals	EN-179484	If you use a Shure microphone in Microsoft Teams mode, you can't unmute a Studio X50 or Studio X30 system using the microphone. You can mute the Studio X50 or Studio X30 system through the user interface, but the local interface still shows the Shure microphone as unmuted.	None.
Peripherals	EN-181948	When you change cameras on your system, the G7500 system web interface doesn't automatically update and display the correct camera model.	Refresh the web browser window.
Peripherals	EN-183942	When connecting an EagleEye IV USB camera to the system, panning and tilting the camera view can be slower than expected.	None.
Peripherals	EN-185265	When you perform a factory restore when your system is running RingCentral Rooms, you are unable to sign in to RingCentral Rooms using a TC8 after the system restarts.	Perform a system update and verify the system and TC8 are running the same software version.
Provisioning	EN-132148	In RealPresence Resource Manager, you can't provision the exchange.meeting.reminderInterval parameter using these permitted configuration values: None, 1, 5, 10, 15, or 30.	Configure this feature using the Meeting Reminder Time in Minutes setting in the system web interface.
Provisioning	EN-157566	The cast.miracast.enforcepin parameter isn't included in the template configuration file you can download from the system.	None.
Provisioning	EN-180125	The exported template file contains errors that causes some parameters to not be provisioned.	Review the template file and modify values before provisioning your system.

Software Update	EN-184370	In Poly Video Mode, the system may go to sleep while TC8 is updating, but the updating process completes successfully.	Adjust the Time Before System Goes to Sleep setting in General Settings > System Settings .
User Interface	EN-132836	In the system web interface, you can't configure 802.1p/Q settings.	Select Enable 802.1p/Q and select Save . The related settings become configurable.
User Interface	EN-162421	On the Studio X50 and Studio X30 local interface, the system hangs on the Discovering Network screen after you factory restore the system.	Verify the system has a network connection before factory restoring the system.
Video	EN-178687	When in Poly Video mode or Poly Partner mode running Zoom, if you send high-quality video from Studio X50 or Studio X30, the video quality is not significantly clearer than 720p.	None.
Video	EN-183983	A green line displays at the bottom of the camera preview and on the far video output during a Microsoft Teams call.	None.
Video	EN-185298	When a G7500 system with a connected HDMI device goes idle, you lose main camera video.	Restart the system.

System Constraints and Limitations

This section provides information on constraints and limitations when using G7500, Studio X50, or Studio X30 systems.

Note: Constraints and limitations apply to all systems unless noted otherwise.

Using the System as a Camera and Audio Peripheral

Note the following limitations when using your system as an external camera, microphone, and speaker in Device Mode:

- Poly Trio systems:
 - When you pair a Trio 8500 or Trio 8800 system, Device Mode works only in Poly Video Mode.
 - When you pair a Trio C60 system, Device Mode works in Poly Video Mode or Partner Mode (when using Zoom).
- System and connected microphone LEDs don't indicate you're muted if you mute using RealPresence Desktop.

Microsoft Teams

Note the following limitations when using Microsoft Teams with a Poly video conferencing system:

- You can't use Teams with a G7500 system.
- You can use only one monitor.
- You can't use your system's HDMI input to share content.
- You can't use your system as an external camera, microphone, and speaker for your laptop in Device Mode.

Starleaf

Note the following limitation when using Starleaf with a Poly video conferencing system:

- You can use only a Polycom EagleEye IV HDCI camera with a G7500 system.

Joining a Password-Protected Zoom Meeting Using Trio C60

If you are in Poly Video Mode using Trio C60 and want to join a password-protected Zoom meeting, you must do one of the following:

- Press the pound sign before entering the meeting password.
- Enter the meeting password as part of the dialing sequence. For example,
`<meetingID>.<password>@zoomcrc.com.`

Poly TC8

When using a Studio X50 system in Poly Video Mode, you can't see an incoming call notification on TC8 when the TC8 displays the **Camera** or **Settings** screen.

Secondary Wi-Fi Network in Partner Mode

You may see the **Wi-Fi Network** menu in the system web interface after switching from Poly Video Mode to Partner Mode. Disable the secondary Wi-Fi network when the system is in Partner Mode.

Sleep and Out of Office Settings in Partner Mode

Configuring sleep and out of office settings with the system web interface may not be supported in Partner Mode. Check your partner application settings for support of similar functionality.

Master Audio Volume in Partner Mode

Configuring the **Master Audio Volume** setting with the system web interface isn't supported in Partner Mode. Change the volume using your partner application settings instead.

Poly EagleEye Cube USB Camera

Note the following when using an EagleEye Cube USB camera with your system:

- The system doesn't support 1080p at 60 fps, but it does support 1080p at 30 fps.
- The system supports only one directly connected camera at a time. For example, you can't connect both an HDCI camera and an EagleEye Cube USB camera.
- The system logs don't include entries about the camera. You can download camera logs using the Polycom Companion application.
- Some camera settings are available only through the Polycom Companion application (for example, hue).
- You can provision camera settings with RealPresence Resource Manager only when you connect the camera to your system.
- If you previously purchased an EagleEye Cube USB camera to use with a Poly Trio system, you can also use the camera with your system. However, to avoid camera connectivity issues with the system, do one of the following to update the camera firmware to at least version 1.1.0-827:
 - Connect the camera to a Poly Trio system running software version 5.9.0AB or later.
 - Update the camera using the Polycom Companion application.

Polycom EagleEye IV HDCI Digital Camera Cable (10 m)

The 10 m (32.8 ft) HDCI cable (part number 2457-64356-101) used to connect an EagleEye IV camera to your G7500 system isn't supported.

If you need to connect your camera up to that distance, use the Polycom EagleEye Digital Extender instead.

Polycom Content App

Since Poly video systems use a minimum of TLS 1.2 by default, Poly recommends that you install Polycom Content App for Windows 1.3.1 or later to avoid issues connecting the client with the system.

Polycom Content App for Mac doesn't currently support TLS 1.2. To use this client, you must configure your system to support a minimum of TLS 1.1.

Miracast-Certified Devices

Note the following when using Miracast-certified devices with the system:

- Windows devices only require a security code during the first attempt to connect to the G7500 system. If you can't connect, you may need to remove the system from your device connection list and try again.
- 4K content sharing isn't supported.

- To confirm you have a Miracast-certified device, search for your device on the [Wi-Fi Alliance website](#).

No Support for HDCP Sources

You can't send content from a High-bandwidth Digital Content Protection (HDCP) source to your system. An HDCP source can be a Blu-ray disc player, DVD player, or similar device.

3.5 mm Audio Input on Studio X50

The 3.5 mm audio input port on Studio X50 systems isn't currently supported. It is reserved for future use.

Poly Microphone IP Adapter

Note the following audio limitations when using the microphone adapter with your G7500 system:

- Polycom Acoustic Fence technology isn't supported.
- The RealPresence Group Series microphone array configuration uses stereo audio by default, but the microphone adapter supports only mono mode.

Checking Factory Restore Progress

When you factory restore your G7500 or Studio X50 system, you can only see the restore progress on a display connected to the secondary monitor HDMI output port.

If you have just one monitor and want to view the restore progress, plug your monitor into the secondary port.

Note: You can't see the restore progress for a Studio X30 system because it has only one monitor connection.

Calibrating the EagleEye Producer

You currently can't calibrate an EagleEye Producer camera connected to your G7500 system for group framing.

Remote Logging and TLS

When your system sends logs to a remote logging server, it may use a version of TLS that you configured your system not to use. This happens because your system sends logs using the TLS version configured on your remote logging server.

For example, if you set your system's minimum version of TLS to 1.2, but the server only uses TLS 1.0, it still receives the logs.

802.1X in IPv6 Environments

In IPv6 environments, Poly video systems and TC8 devices don't support 802.1x authentication. 802.1x is supported only for IPv4 networks.

Secure Media Streams

Media streams (audio, video, and content) over HTTPS aren't supported.

Sharing Content with RealPresence Desktop

You can't share content to a system using the RealPresence Desktop for Windows or Mac application.

Video Color

Color reproduction accuracy can vary depending on environmental conditions and camera sensor capabilities.

Video Noise from Studio X50 and Studio X30

When the room lighting is lower than 200 lx, you may see video noise in the video sent from Studio X50 or Studio X30.

Interoperability

This section includes supported peripherals and products tested with this release.

Note: Peripherals are supported in Poly Video Mode and Poly Partner Mode unless noted otherwise.

Supported G7500 Peripherals and Applications

G7500 systems support the following peripherals and applications:

- Poly TC8
- Poly Trio C60, Poly Trio 8500, and Poly Trio 8800
- Poly IP Table Microphone
- Poly IP Ceiling Microphone
- Poly Microphone IP Adapter
- Polycom RealPresence Group Series table and ceiling microphone arrays (connected using the microphone adapter)
- Polycom SoundStructure accessory (with microphone adapter connection)
- Polycom Stereo Speaker Kit

-
- Shure IntelliMix P300 audio conferencing processor
 - Poly EagleEye Cube USB camera
 - Poly Studio USB video bar
 - Polycom EagleEye Mini USB camera
 - Polycom EagleEye IV camera
 - Polycom EagleEye Director II camera (HDCI connections only)
 - Polycom EagleEye Producer camera
 - Polycom EagleEye Digital Extender
 - Poly Bluetooth Remote Control
 - Polycom Content App (Poly Video Mode only)
 - Zoom Rooms
 - GoToRoom by LogMeIn
 - 8x8
 - StarLeaf
 - RingCentral Rooms

Supported Studio X50 Peripherals and Applications

Studio X50 systems support the following peripherals and applications:

- Poly TC8
- Poly Trio C60, Poly Trio 8500, and Poly Trio 8800
- Polycom RealPresence Debut expansion microphone
- Shure IntelliMix P300 audio conferencing processor
- Poly Bluetooth Remote Control
- Poly EagleEye Cube USB camera
- Poly Studio USB video bar
- Polycom EagleEye IV USB camera
- Polycom EagleEye Mini USB camera
- Polycom Content App (Poly Video Mode only)
- Zoom Rooms
- Microsoft Teams
- GoToRoom by LogMeIn
- 8x8
- StarLeaf
- RingCentral Rooms

Supported Studio X30 Peripherals and Applications

Studio X30 systems support the following peripherals and applications:

- Poly TC8
- Poly Trio C60, Poly Trio 8500, and Poly Trio 8800
- Poly Bluetooth Remote Control
- Polycom Content App (Poly Video Mode only)
- Zoom Rooms
- Microsoft Teams
- GoToRoom by LogMeIn
- 8x8
- StarLeaf
- RingCentral Rooms

Supported Browsers

You can access the system web interface with the following browsers:

- Google Chrome 46.0.2490.86 and later
- Apple Safari 9 and later
- Mozilla Firefox 42.0 and later
- Microsoft Edge 17 and later

Products Tested with This Release

G7500, Studio X50, and Studio X30 systems are tested extensively with a wide range of products. The following list is not a complete inventory of compatible equipment. It indicates the products that have been tested for compatibility with this release.

Note: Poly recommends that you upgrade your Poly devices with the latest software versions, as compatibility issues may already have been addressed by software updates. See the [Current Polycom Interoperability Matrix](#) to match product and software versions.

External MCU, Call Managers, Recorders, Gatekeepers, and Gateways

Product	Tested Versions
Poly One Touch Dial Service	Current version
Poly RealConnect Service	Current version
Polycom RealPresence Collaboration Server 1800/2000/4000/Virtual Edition	8.8.1 8.9.0

Polycom RealPresence DMA 7000, Appliance and Virtual Editions	10.0.0
Polycom RealPresence Resource Manager, Virtual Edition	10.8.0
Polycom RealPresence Media Suite	2.8.2
Cisco Telepresence Video Communication Server	X12.5.7

Poly Endpoints

Product	Tested Versions
Polycom RealPresence Group Series	6.2.2.3
Poly G200	1.2.0
Poly G7500, Poly Studio X50, and Poly Studio X30 with Poly Trio C60, Poly Trio 8500, and Poly Trio 8800	Poly VideoOS software 3.2.0 UC software 5.9.4
Polycom HDX 7006/8006/9006	3.1.14
Polycom RealPresence Desktop for Windows	3.10.4
Polycom RealPresence Desktop for Mac	3.10.4
Polycom RealPresence Mobile for Apple iOS	3.11.1
Polycom RealPresence Mobile for Android	3.10.1
Poly Trio C60, Poly Trio 8500, and Poly Trio 8800	5.9.4
Poly Trio 8500 and Poly Trio 8800 with Polycom RealPresence Group Series	UC software 5.9.4 RealPresence Group Series software 6.2.2.3
Poly Trio Visual+	5.9.4
Poly Trio VisualPro	UC software 5.9.4 RealPresence Group Series software 6.2.2.3
Polycom RealPresence Debut	1.3.3
Polycom VVX 450/501/601	5.9.5.0614 6.3.0.14929

Third-Party Endpoints

Product	Tested Versions
Avaya Scopia XT7000 and XT5000	v9_2_0_215
Cisco C90, C40, and C20	TC7.3.21.6ac6d47
Cisco SX80, SX20, and SX10	CE9.13.0 990355df13a
Huawei DP-300	2.00.b00

Huawei TE40 and TX50	6.10.0
LifeSize ICON 450/600/800i	3.4.0(2268)

Peripherals and Applications

Product	Tested Versions
Poly EagleEye Cube USB	1.3.0
Polycom EagleEye Director II	2.2.0.39
Polycom EagleEye Producer	1.2.2.2
Polycom EagleEye IV USB	1.2.1
Polycom EagleEye USB Mini	9.0.23
Poly Studio	1.3.0
Poly IP Table Microphone	3.0.0
Poly IP Ceiling Microphone	3.0.0
Poly Microphone IP Adapter	3.0.0
Poly TC8	3.2.0
Poly Lens	Current version
Polycom Content App	1.3.3
Zoom Rooms	5.1.2
GoToRoom by LogMeIn	1.0.69

Get Help

For more information about installing, configuring, and administering Poly products or services, go to the [Poly](#) site, click Support, and choose the option best suited to your needs.

Related Poly and Partner Resources

See the following sites for information related to this product.

- The [Poly Online Support Center](#) is the entry point to online product, service, and solution support information including Licensing & Product Registration, Self-Service, Account Management, Product-Related Legal Notices, and Documents & Software downloads.
- The [Polycom Document Library](#) provides support documentation for active products, services, and solutions. The documentation displays in responsive HTML5 format so that you can easily access and view installation, configuration, or administration content from any online device.

- The [Polycom Community](#) provides access to the latest developer and support information. Create an account to access Poly support personnel and participate in developer and support forums. You can find the latest information on hardware, software, and partner solutions topics, share ideas, and solve problems with your colleagues.
- The [Polycom Partner Network](#) are industry leaders who natively integrate the Poly standards-based RealPresence Platform with their customers' current UC infrastructures, making it easy for you to communicate face-to-face with the applications and devices you use every day.
- The [Polycom Collaboration Services](#) help your business succeed and get the most out of your investment through the benefits of collaboration.

Copyright and Trademark Information

© 2020 Plantronics, Inc. All rights reserved. No part of this document may be reproduced, translated into another language or format, or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Plantronics, Inc.

Plantronics, Inc. (Plantronics + Polycom, Now together as Poly)

345 Encinal Street

Santa Cruz, California

95060

Poly and the propeller design are trademarks of Plantronics, Inc. All other trademarks are the property of their respective owners.

Patent Information

The accompanying product may be protected by one or more U.S. or foreign patents and/or pending patent applications held by Polycom, Inc.

Disclaimer

This software is provided 'as is' with no explicit or implied warranties in respect of its properties, including, but not limited to, correctness and fitness for purpose.