



Polycom® UC Software 5.4.1 Rev I

Applies to the Polycom VVX® Business Media Phones and Polycom SoundStructure® VoIP Interface

Contents

What's New in Polycom UC Software 5.4.1 Rev I	2
Release History	5
Security Updates	6
Install UC Software 5.4.1 Rev I	7
Resolved Issues	10
Known Issues	10
Updates to Previous Software Releases	11
Get Help	22
Copyright and Trademark Information	23

What's New in Polycom UC Software 5.4.1 Rev I

Polycom® Unified Communications (UC) Software 5.4.1 Rev I is a release for Polycom for all Open SIP servers along with Microsoft® Lync 2010, Lync 2013, Skype™ for Business, and Skype™ for Business Online interoperability.

Polycom UC Software 5.4.1 Rev I supports the following Polycom endpoints:

- Polycom® VVX® 101 business media phones
- Polycom® VVX® 201 business media phones
- Polycom® VVX® 300/310 business media phones
- Polycom® VVX® 301/311 business media phones
- Polycom® VVX® 400/410 business media phones
- Polycom® VVX® 401/411 business media phones
- Polycom® VVX® 500 business media phones
- Polycom® VVX® 501 business media phones
- Polycom® VVX® 600 business media phones
- Polycom® VVX® 601 business media phones
- Polycom® SoundStructure VoIP Interface
- Polycom® VVX® 1500 business media phones

Polycom UC Software 5.4.1 Rev I supports the following Polycom accessories:

- Polycom® VVX® Camera
- Polycom® VVX® Expansion Module

These release notes provide important information on software updates, phone features, and known issues.

New Display Component on VVX 500 Business Media Phones

VVX 500 business media phones manufactured as of May 2017 are being shipped with the new display component from a secondary component vendor. When the VVX 500 business media phone encounters an incompatible version of UC software on the provisioning server that does not support the new component, the phone installs the UC software and you may experience a flicker. This release includes a software change that makes it compatible with the new display component.

Important Notice

Due to the increase in size of the software code base in UCS 5.4.1 Rev I, an issue has been found when upgrading to UCS 5.4.1 Rev I using the combined image. This issue may prevent phones from upgrading successfully. Phone administrators utilizing the combined image files should perform one of the following upgrade types.

Upgrade to UCS 5.2.5 prior to upgrading to UCS 5.4.1 Rev I. This fix will also be made available in UCS 5.3.3.

- Upgrade to UCS 5.4.1 Rev I using the individual split images.



Note: Attempting to upgrade directly to UCS 5.4.1 Rev I will not harm the phone, and the upgrade may succeed. However, this is not recommended. Applying future upgrades to phones running UCS 5.4.1 Rev I will not require any special action.

Phone Features and Licenses

The features and licenses required to operate the phones vary by phone model. Refer to this section to find out which phone features and licenses you require for your phone model.

The following table describes features available for each phone and indicates whether a feature license is required. In the following table, *No* indicates that a phone does not support a feature, *Yes* indicates that a phone supports a feature and no license is required, and *Yes** indicates that the phone requires you to purchase a feature license from Polycom to support a feature.

VVX Series Features and Licenses

Feature	VVX 101	VVX 201	VVX 300/310	VVX 301/311	VVX 400/410	VVX401/411	VVX 500/501	VVX 600/601	VVX 1500	Sound Structure VoIP Interface
VQMon	Yes*	Yes*	Yes*	Yes*	Yes*	Yes*	Yes (Audio only)	Yes (Audio only)	Yes (Audio only)	No
Server Based Call Recording	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
USB Call Recording	No	No	No	Yes	No	Yes	Yes	Yes	Yes	No
Conference Management	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Electronic Hookswitch	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Enhanced Feature Keys	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Customizable UI Background	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Asian Languages	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No

<i>Feature</i>	<i>VVX 101</i>	<i>VVX 201</i>	<i>VVX 300/ 310</i>	<i>VVX 301/ 311</i>	<i>VVX 400/ 410</i>	<i>VVX401/ 411</i>	<i>VVX 500/ 501</i>	<i>VVX 600/ 601</i>	<i>VVX 1500</i>	<i>Sound Structure VoIP Interface</i>
Enhanced BLF	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
H.323 Video	No	No	No	No	No	No	Yes	Yes	Yes	No

*You must purchase a feature license from Polycom.

Supported DHCP Sub-Options

The following table lists the individual sub-options and combination sub-options supported on VVX phones for DHCP Option 43.

DHCP Option 43 Configuration Options

<i>Option</i>	<i>Result</i>
Option 1 - Subnet mask	The phone parses the value from Option 43
Option 2 - Time offset	The phone parses the value.
Option 3 - Router	The phone parses the value.
Option 4 - Time server	The phone parses the value.
Option 6 - Domain Name Server	The phone parses the value.
Option 7 - Domain Log server	The phone parses the value.
Option 15 - Domain Name	The phone parses the value.
Option 42 - Network Time Protocol server	The phone parses the value.
Option 66 - TFTP Server Name	The phone parses the value.
Sub-options configured in Option 43	
Options 1, 2, 3, 4, 5, 6, 7, 15, 42, and 66	The phone parses the value.

Release History

The following table shows the recent release history of Polycom Unified Communications (UC) Software.

Release History

<i>Release</i>	<i>Release Date</i>	<i>Description</i>
5.4.1 Rev I	April 2017	New software change on VVX 500 business media phones to support new LCD panel on the phones.
5.4.1 Rev F	May 2016	This release includes an important field fix.
5.4.1	December 2015	This release includes support for the following features: <ul style="list-style-type: none"> • Flexible line key customization for Lync (EFLK) • Master Key Identifiers (MKI) • Shared Line appearance on Lync • BToE for Windows 10 • Smart Search for Lync ABS • Support for simplified Chinese font on VVX 101
5.4.0A	September 2015	<ul style="list-style-type: none"> • Microsoft Office 365 and Skype for Business Online • Office365 and Skype for Business Provisioning and Manageability • Time and Date Initial Setup
5.4.0	May 2015	<p>Added support for Alcatel-Lucent CTS features including</p> <ul style="list-style-type: none"> • Advanced Conference • Shared Call Appearance with Bridge In • Visitor Desk Phone <p>This release also included support for the following features:</p> <ul style="list-style-type: none"> • Barge In on Busy Lamp Field Lines • DTMF Relay • SIP Instance • Comfort Noise • Opus Codec • DNS Server Address Override • Global Directory Synchronization • Basic Menu Lock • Additional features including user interface improvements and resolved known issues.
5.3.2	November 2015	This release has important field fixes.
5.3.1	July 2015	Includes support for locking the settings menu, enhancements for push-to-talk calls, support for Lync location-based routing, and other important field fixes.

<i>Release</i>	<i>Release Date</i>	<i>Description</i>
5.3.0	March 2015	Includes support for several Lync, BroadSoft, and Open SIP features.
5.2.5	December 2015	Includes support for new in call display and off hook dialing as well as critical field fixes.
5.2.4	September 2015	This release delivers important field fixes.
5.2.3	May 2015	This release has important field fixes.
5.2.2	March 2015	This release has important field fixes. Minor feature improvements, an added Open Source Software license, and other resolved issues.
5.2.1	November 2014	This release has important field fixes.
5.2.0	October 2014	Added support for web page sign-in to Lync, user interface optimizations, and support for various GENBAND features.
5.1.3	November 2014	Added support to log into Lync client through the phone's web interface.
5.1.2	September 2014	Added image background lock down and power turn off for all the USB ports.
5.1.1C	July 2014	Introduced Microsoft-qualified UC Software for VVX 410, VVX 500, VVX 600, and SoundStructure VoIP Interface.
5.1.1B	July 2014	Resolved the bandwidth hold issues that existed on VVX 300 phones and SoundStructure VoIP Interface when using Lync 2013 with Call Admission Control.
5.1.1	July 2014	Added full support of Lync contact card and support to forward the delegated call to the boss voicemail.
5.1.0	May 2014	Added visual indication of security classification, centralized call recording controls for BroadSoft server, and enabling or disabling the security vulnerable ports.
5.0.1	October 2013	Added Arabic language support, BToE auto pairing, quick search support for the BroadSoft UC-One local contacts.
5.0.0	September 2013	Added support to Lync Call Park feature, Better Together over Ethernet (BToE), Lync Boss-Admin, and Address Book Services (ABS).

Security Updates

Refer to the [Polycom Security Center](#) for information about known and resolved security vulnerabilities.

Install UC Software 5.4.1 Rev I

Consider the following installation and update information when using Polycom UC Software 5.4.1 Rev I.

Download the Distribution Files

To download UC Software 5.4.1 Rev I, you can choose the combined UC Software package or the split UC Software package, both in ZIP file format. The combined version contains all files for all phone models. The split software package is smaller, downloads more quickly, and contains sip.ld files for each phone model, enabling you to choose provisioning software for your phone model and maintain software versions for each model in the same root directory.

For general use, Polycom recommends using the split resource file that corresponds to the phone models for your deployment. To match the correct UC software resource file to your phone model, see the table [Understand the Combined ZIP and Split ZIP Files](#). If you are provisioning your phones centrally using configuration files, download the corresponding resource file and extract the configuration files to the provisioning server, maintaining the folder hierarchy in the ZIP file.

The current build ID for the sip.ld and resource files is **5.4.1.18405**.

Understand the Combined and Split ZIP Files

To understand the files distributed in the combined ZIP file, refer to the following table.

Understand the Combined ZIP and Split ZIP Files

Distributed Files	File Purpose and Application	Combined ZIP	Split SIP
3111-40250-001.sip.ld	SIP application executable for VVX 101	x	✓
3111-40450-001.sip.ld	SIP application executable for VVX 201	x	✓
3111-46135-002.sip.ld	SIP application executable for VVX 300	x	✓
3111-48300-001.sip.ld	SIP application executable for VVX 301	x	✓
3111-46161-001.sip.ld	SIP application executable for VVX 310	x	✓
3111-48350-001.sip.ld	SIP application executable for VVX 311	x	✓
3111-46157-002.sip.ld	SIP application executable for VVX 400	x	✓
3111-48400-001.sip.ld	SIP application executable for VVX 401	x	✓
3111-46162-001.sip.ld	SIP application executable for VVX 410	x	✓
3111-484500-001.sip.ld	SIP application executable for VVX 411	x	✓

Distributed Files	File Purpose and Application	Combined ZIP	Split SIP
3111-44500-001.sip.ld	SIP application executable for VVX 500	x	✓
3111-48500-001.sip	SIP application executable for VVX 501	x	✓
3111-44600-001.sip.ld	SIP application executable for VVX 600	x	✓
3111-48600-001.sip	SIP application executable for VVX 601	x	✓
2345-17960-001.sip.ld	SIP application executable for VVX 1500	x	✓
3111-33215-001.sip.ld	SIP application executable for SoundStructure VoIP Interface	x	✓
sip.ld	Concatenated SIP application executable	✓	x
sip.ver	Text file detailing build-identification(s) for the release	✓	✓
000000000000.cfg	Master configuration template file	✓	✓
000000000000-directory~.xml	Local contact directory template file. To apply for each phone, replace the (zeroes) with the MAC address of the phone and remove the ~ (tilde) from the file name	✓	✓
applications.cfg	Configuration parameters for microbrowser and browser applications	✓	✓
features.cfg	Configuration parameters for telephony features	✓	✓
firewall-nat.cfg	Contains configuration parameters for telephony features	✓	✓
H323.cfg	Configuration parameters for the H.323 signaling protocol	✓	✓
lync.cfg	Contains Lync specific configuration parameters	✓	✓
pstn.cfg	Contains parameters for PSTN use	✓	✓
reg-advanced.cfg	Contains configuration parameters for the line and call registration and advanced phone feature settings	✓	✓
reg-basic.cfg	Configuration parameters for line and call registration and basic phone settings	✓	✓

Distributed Files	File Purpose and Application	Combined ZIP	Split SIP
region.cfg	Configuration parameters for regional and localization settings such as time and date and language	✓	✓
sip-basic.cfg	Configuration parameters for the VoIP server and softswitch registration	✓	✓
sip-interop.cfg	Configuration parameters for the VoIP server, softswitch registration, and interoperability configuration	✓	✓
site.cfg	Configuration parameters that are set for each site	✓	✓
video.cfg	Configuration parameters for video connectivity	✓	✓
video-integration.cfg	Configuration parameters for SoundStation IP 7000 and Polycom HDX system integration	✓	✓
VVX-dictionary.xml	Includes native support for the following languages: <ul style="list-style-type: none"> • Chinese, Traditional • Chinese, Simplified • Danish, Denmark • Dutch, Netherlands • English, Canada • English, United Kingdom • English, United States • French, Canada • French, France • German, Germany • Italian, Italy • Japanese, Japan • Korean, Korea • Norwegian, Norway • Polish, Poland • Portuguese, Brazil • Russian, Russia • Slovenian, Slovenia • Spanish, Spain • Swedish, Sweden • Arabic, UAE 	✓	✓
Welcome.wav	Startup welcome sound effect	✓	✓

Distributed Files	File Purpose and Application	Combined ZIP	Split SIP
LoudRing.wav	Sample loud ringer sound effect	✓	✓
Warble.wav	Sample ringer sound effect	✓	✓

Resolved Issues

There are no resolved issues for the UC Software 5.4.1 Rev I release.

Known Issues

This section lists the known issues and suggested workarounds for this release and previous releases.

Known Issues and Suggested Workarounds for UC Software 5.4.1 Rev I

Category	Issue No.	Release	Description	Workaround
Expansion Modules	VOIP-107913	5.4.1	Expansion Modules may go into a reboot loop and may not come up if they are unplugged from the host phone while they are in the process of being upgraded.	Wait 2 seconds for paper and 15 seconds for LCD Expansion Module before unplugging.
General	VOIP-108028	5.4.1	On the VVX 600 phone, after attaching a headset, the pop-up stating the device has connected successfully appears twice.	.
General	VOIP-104994	5.4.1	The user is unable to exit to the Home screen from the LAN port diagnostic and PC port diagnostic screens when the Home button is pressed.	Press the home button twice.
General	VOIP-105796	5.4.1	In VVX 5XX/6XX phones, Automatic Login using Pin Extension in will not work first time after a reboot when the credentials are provided from a configuration file.	The VVX 5XX/6XX phones need manual input before accepting the Pin Authentication credentials from the Config file.

Updates to Previous Software Releases

This section describes new features and enhancements to previous UC Software releases.

What's New in Polycom UC Software 5.4.1 Rev F

This section lists a new resolved issue.

Resolved Issues

This section lists the issues that were resolved in UC Software 5.4.1 Rev F.

Resolved Issues in 5.4.1 Rev F

<i>Category</i>	<i>Issue No.</i>	<i>Release</i>	<i>Description</i>
General	VOIP-117118	5.5.0	The phone upgrade through Voice VLAN now works without any issue.

What's New in Polycom UC Software 5.4.1

Polycom® Unified Communications (UC) Software 5.4.1 is a release for Polycom for all Open SIP servers along with Microsoft® Lync 2010, Lync 2013, Skype™ for Business, and Skype™ for Business Online interoperability. UC Software 5.4.1 is the first release to support the new VVX 301, 311, 401, 411, 501, and 601 business media phones.

Polycom UC Software 5.4.1 supports the following Polycom endpoints:

- VVX 101 business media phones
- VVX 201 business media phones
- VVX 300/310 business media phones
- VVX 301/311 business media phones (new phones introduced in this release)
- VVX 400/410 business media phones
- VVX 401/411 business media phones (new phones introduced in this release)
- VVX 500 business media phones
- VVX 501 business media phones (new phones introduced in this release)
- VVX 600 business media phones
- VVX 601 business media phones (new phones introduced in this release)
- SoundStructure VoIP Interface
- VVX 1500 business media phones

Polycom UC Software 5.4.1 supports the following Polycom accessories:

- Polycom® VVX® Camera

- Polycom® VVX® Expansion Module

These release notes provide important information on software updates, phone features, and known issues.

Important Notice

Due to the increase in size of the software code base in UCS 5.4.1, an issue has been found when upgrading to UCS 5.4.1 using the combined image. This issue may prevent phones from upgrading successfully. Phone administrators utilizing the combined image files should perform one of the following upgrade types.

- Upgrade to UCS 5.2.5 prior to upgrading to UCS 5.4.1. This fix will also be made available in UCS 5.3.3.
- Upgrade to UCS 5.4.1 using the individual split images.

NOTE: Attempting to upgrade directly to UCS 5.4.1 will not harm the phone, and the upgrade may succeed. However, this is not recommended. Applying future upgrades to phones running UCS 5.4.1 will not require any special action.

New Features

Polycom UC Software 5.4.1 includes the features and functionality of previous releases and includes the following new features:

- Enhanced Flexible Line Key (EFLK) customization for Skype for Business
- Master Key Identifier (MKI)
- Shared Line Appearance for Lync (SLA)
- Support for Simplified Chinese font on VVX 101
- Support for Better Together over Ethernet (BToE) on Windows 10®
- Smart Search for Lync Address Book Service
- Incoming Call Handling for Locked Phones for Lync/Skype for Business
- Global Directory Synchronization

Enhanced Flexible Key Line Customization for Lync (EFLK)

The Enhanced Flexible Line Key feature is now supported for users in a Lync environment using the Polycom VVX line of business media phones, facilitating workflow and greater ease of use. This feature is not supported on VVX 101, 201, and 1500 business media phones.

In Default mode, Polycom VVX Business Media phones display registrations and other contacts in the following order:

- Registration
- SLA Lines/ Boss contacts
- Pinned contacts
- Favorites (Local contacts)

In Customized mode, users can assign/customize contacts to each line.

EFLK functionality enables you to assign up to 100 customized contacts to unassigned lines; clear any contact assigned to a line; delete contacts; insert an empty line above or below the selected line key; and search and assign any local or Lync contact to an unassigned line.

The EFLK feature is disabled by default. You can configure the following parameters to enable EFLK functionality on supported phones:

- `feature.flexibleLineKey.enable`

See the section [Configuration File Enhancements](#) for permitted values and descriptions for this parameter.

Master Key Identifiers (MKI)

VVX Business Media Phones now support encryption (crypto) with or without Master Key Identifiers (MKI) in the offered Session Description Protocol (SDP). The following parameter enables administrators to select encryption with or without MKI while establishing a call.

Also a VVX Business Media Phones can now establish an audio call when it receives an offer crypto in SDP without MKI even when this feature is enabled.

Users can configure the following parameters to enable MKI functionality on supported phones:

- `sec.srtp.mki.enabled`

See the section [Configuration File Enhancements](#) for permitted values and descriptions for this parameter.

Shared Line Appearance for Skype for Business (SLA)

This feature enables you to join a common call group sharing the same line registration. Each shared line can receive only one incoming call at a time. You cannot make outgoing calls from the shared line, neither can you make 911 emergency calls. Conference calls, BTOE, and the Call Park feature are not supported on SLA lines, and are available on the user's primary line.

An incoming call to the shared line is received by all phones sharing the line. After the call is answered, anyone sharing the line can view the call state, or pick up the call if another user places it on hold. Barge-in is not supported on Microsoft-registered phones.

This feature is not supported on VVX 101 or 1500 business media phones.

Note that you must install the Shared Line Application on the Microsoft Front End server and configure SLA groups in Windows Powershell.

You can configure a ring tone type using a parameter, and users can set a ring type from the phone menu system at: **Settings > Basic > RingType > SLA Ring type**.

See the section [Configuration File Enhancements](#) for permitted values and a description for this parameter.



Note: Conference, BTOE, and Call park features are not supported for SLA lines. Please note that these features are only available on the primary line.

Better Together over Ethernet for Windows 10

Better Together over Ethernet (BToE) is now supported on Microsoft® Windows® 10.

Smart Search for Skype for Business Address Book Service

VVX phones registered with Skype for Business now offer predictive search when searching for contacts in the Skype for Business Address Book Service. You can choose to search by number or press the ABC soft key to enable predictive alphabetical search.

Answer Incoming Calls on a Locked Phone in Lync/Skype for Business

You can allow users to answer incoming calls on a locked phone when deployed in a Lync/Skype for Business environment. Administrators can configure phones registered with Skype for Business to display an Answer soft key that displays when a locked phone receives an incoming call. When users answer a call with the Answer soft key, an Unlock and End Call soft key displays. Users can lock or unlock the phone at any time.

Users cannot make outgoing calls until a phone is unlocked. Conferences, Call Park, and Call Transfer are not available until a user unlocks the phone.

See the section [Configuration File Enhancements](#) for permitted values and a description for this parameter.

Global Directory Synchronization

You can now download the <MAC>-directory.xml and 000000000000-directory.xml files. Both these files are needed to build the local contact directory.

Any contacts that you add, update, or save locally are uploaded to the <MAC>-directory.xml file.

See the section [Configuration File Enhancements](#) for permitted values for this parameter.

Additional Features in This Release

The following feature enhancements were made for this UC Software 5.4.1 release:

- Do Not Store Browser Page Context When the Browser is Opened
- Remove QSetup Fields Based on Configuration. See [Configuration File Enhancements](#)
- Support Sending SUBSCRIBE for message-summary/MWI on SCA

Phone Features and Licenses

The features and licenses required to operate the phones vary by phone model. Refer to this section to find out which phone features and licenses you require for your phone model.

The following table describes features available for each phone and indicates whether a feature license is required. In the following table, *No* indicates that a phone does not support a feature, *Yes* indicates that a phone supports a feature and no license is required, and *Yes** indicates that the phone requires you to purchase a feature license from Polycom to support a feature.

VVX Series Features and Licenses

<i>Feature</i>	<i>VVX 101</i>	<i>VVX 201</i>	<i>VVX 300/ 310</i>	<i>VVX 301/ 311</i>	<i>VVX 400/ 410</i>	<i>VVX401/ 411</i>	<i>VVX 500/ 501</i>	<i>VVX 600/ 601</i>	<i>VVX 1500</i>	<i>Sound Structure VoIP Interface</i>
VQMon	Yes*	Yes*	Yes*	Yes*	Yes*	Yes*	Yes (Audio only)	Yes (Audio only)	Yes (Audio only)	No
Server Based Call Recording	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
USB Call Recording	No	No	No	Yes	No	Yes	Yes	Yes	Yes	No
Conference Management	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Electronic Hookswitch	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Enhanced Feature Keys	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Customizable UI Background	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Asian Languages	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
Enhanced BLF	No	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	No
H.323 Video	No	No	No	No	No	No	Yes	Yes	Yes	No

*You must purchase a feature license from Polycom.

Configuration File Enhancements

The following table lists configuration file enhancements that include new or changed parameters for this Polycom UC Software 5.4.1 release. For more information on using configuration parameters to enable or

disable features, see the *Administrator Guide for Polycom UC Software 5.4* available on the [Polycom Voice Support](#) site.

Configuration File Enhancements in UC Software 5.4.1

<i>Parameter</i>	<i>Permitted Values</i>	<i>Default</i>
call.shared.remoteActiveHoldAsActive	0 or 1	1
If 1, both remote hold and remote active calls are treated as active calls on the phone. If 0, both remote hold and remote active calls are not treated as active calls on the phone.		
device.sntp.serverName	0 or 1	0
If 1, an alternate SNTP server address will be used when the DHCP's SNTP Server (received from the DHCP server) is not present and the SNTP Server (set to tcplpApp.sntp.address) is empty.		
feature.flexibleLineKey.enable	1 and 0	0
If 1, allows users to enable the EFLK feature on the phone. If 0, the feature is disabled. If enabled, EFLK is active on both the host phone and the expansion module.		
log.level.change.flk	0 or 1	0
If 1, users can set the log level for Microsoft EFLK logs. If 0, the feature is disabled.		
phoneLock.Allow.AnswerOnLock	0 or 1	0
If 0, default phone lock behavior is applied. If 1, an Answer soft key displays to allow users to answer incoming calls on locked phones.		
prov.quickSetup.limitServerDetails	0 or 1	0
If 1, user is prompted to enter user name and password, and the system supplies other required information such as DHCP option, server address, and server type from ztp/dhcp (option66). If 0, the user must enter all required information.		
regOnPhone	0 or 1	0
If 1, contacts users assign to a line key are pushed to the attached expansion module. If 0, contacts return to the position the user assigned on the phone line keys.		
sec.srtp.mki.enabled	0 or 1	OpenSIP=0 Lync=1
If 1, the Polycom phone offers two cryptos in the SDP offer, one without an MKI, and one with a four-byte MKI parameter in the SDP message of the SIP INVITE / 200 OK. If 0, Polycom phone offers only one non-MKI crypto in the SDL offer.		
tcplpApp.sntp.address	0 or 1	0
If 1, SNTP server address will be used when DHCP's SNTP Server (received from the DHCP server) is not present or the tcplpApp.sntp.address.overrideDHCP is set to 1.		
tcplpApp.sntp.address.overrideDHCP	0 or 1	0
If 1, determines whether the SNTP Server address should override the DHCP SNTP server.		

<i>Parameter</i>	<i>Permitted Values</i>	<i>Default</i>
up.SLA.ringType	0 or 1	1
<p>If 1, sets the ring type for the shared line so that users can distinguish among incoming calls to a private, primary line and the group SLA line. Note that users can set this ring type from the phone menu system which overrides the value you set here.</p>		
volpProt.SIP.newCallOnUnRegister	0 or 1	1
<p>If 0, the phone does not generate new call-ID and From tag during re-registration.</p>		
volpProt.SIP.specialEvent.checkSync.downloadDirectory	0 or 1	0
<p>If 1, the phone downloads both the <MAC>-directory.xml & 000000000000-directory.xml along with the other configuration files. The local contact directory is created from both these files.</p>		

Supported DHCP Sub-Options

The following table lists the individual sub-options and combination sub-options supported on VVX phones for DHCP Option 43.

DHCP Option 43 Configuration Options

<i>Option</i>	<i>Result</i>
Option 1- Subnet mask	The phone parses the value from Option 43
Option 2 - Time offset	The phone parses the value.
Option 3 - Router	The phone parses the value.
Option 4 - Time server	The phone parses the value.
Option 6 - Domain Name Server	The phone parses the value.
Option 7 - Domain Log server	The phone parses the value.
Option 15 - Domain Name	The phone parses the value.
Option 42 - Network Time Protocol server	The phone parses the value.
Option 66 - TFTP Server Name	The phone parses the value.
Sub-options configured in Option 43	
Options 1, 2, 3, 4, 5, 6, 7, 15, 42, and 66	The phone parses the value.

Resolved Issues

This section lists the issues that were resolved in UC Software 5.4.1.

Resolved Issues in 5.4.1

<i>Category</i>	<i>Issue No.</i>	<i>Release</i>	<i>Description</i>
Audio	VOIP-105578	5.3.1	The phone no longer displays the PC Audio screen when BToE is out of sync.
Audio	VOIP-107424	5.3.0	Inbound audio no longer experiences any cutting out while buddy watching user's own extension.
BToE	VOIP-106212	5.3.1	When BToE is activated and receiving calls from the Response group, the phone now displays the name and number correctly.
Busy Lamp Field	VOIP-101729	5.3.0	A problem was resolved that caused the Busy Lamp Field (BLF) to display incorrectly.
Calling	VOIP-102296	5.3.0	An issue was resolved that caused problems with calling a UC-One contact from a Shared Call Appearance line with URL dialing enabled.
Calling	VOIP-108207	5.4.0	Receiving a PTT or Talk event on the VVX 500 and 600 during away / inactive state no longer causes the phone to set status back to available once the PTT/TALK is finished.
Calling	VOIP-106603 VOIP-106123	5.4.0	In a UC-One deployment, a number having + as prefix in the INVITE message now establishes the call successfully when work number is dialed-out.
Calling	VOIP-106543	5.3.0	The phone now successfully transfers a call establishes two-way audio with no issues while initiating a transfer multiple times.
Calling	VOIP-106341	5.2.2	In a Lync Shared Line Appearance, placing a third call on a VVX 300 is now available and no longer causes any issues.
Contact Directory	VOIP-102294	5.3.0	The phone now correctly displays the extension separately from the phone number in the UC-One directory.
General	VOIP-108547	5.4.0	The VVX 500 no longer logs out the user intermittently with EXT/PIN on a 500 Internal Server Error but gracefully discards it.
General	VOIP-108288	5.3.1	The VVX primary Admin pickup/presence no longer fails after the server goes in to Survivable Mode.
General	VOIP-108097	5.4.0	The phone no longer automatically places the active call on hold when it receives a second incoming call.
General	VOIP-107939	5.4.0	Users are now able to retrieve a private parked call with no issues.

<i>Category</i>	<i>Issue No.</i>	<i>Release</i>	<i>Description</i>
General	VOIP-107815	5.4.0	PIN Authentication now works automatically when set up using the configuration files.
General	VOIP-107786	5.3.0	The phone now ignores the CDP packets without VLAN information.
General	VOIP-107737	5.4.0	The Lync Address book search is working with First and Last name search and matches with previous software behavior.
General	VOIP-107669	5.3.0	Receiving VLAN via LLDP from the Extreme switch no longer causes any issues when the lldpFastStartCount parameter is configured.
General	VOIP-107278	5.3.1	A Boss Voice Mail transfer now works correctly for Boss names that contain a special character.
General	VOIP-106618	5.3.1	The phone no longer reboots upon signout if <code>feature.callList.enabled</code> is set to 0.
General	VOIP-106261	4.1.5	The phone now displays an incoming call alert without any issue if call forwarding is disabled and the indefinite ringing setting is enabled.
General	VOIP-105972	5.3.1	In a Bridged Line Appearance (BLA) scenario, the phone now successfully resumes a remote call.
General	VOIP-104828	5.4.1	The phone now picks up the remote hold call without issue when the far end PSTN number's display name has spaces included in it.
General	VOIP-104360	5.3.0	The phone now sends subscribe to all 64 contacts and updates their presence.
General	VOIP-104340	5.3.0	Selecting a Music on Hold (MOH) filename from the config parameter <code>Feature.moh.filename</code> now works as expected.
General	VOIP-103880	5.4.1	Support for parsing DHCP Option 43, sub-options 128 to 254 for use as a custom boot server has now been added.
General	VOIP-103131	5.3.0	Clicking the Select button in the VVX410 system's caller list now transfers a call with a single click.
General	VOIP-102493	5.3.0	A problem was resolved that caused the phone to occasionally sign the user out in some environments.
General	VOIP-107929	5.3.0	Help and label displayed for configuring the SNTP server address has been modified.
General	VOIP-98498	5.2.0	When the Simultaneously Ring to My Team Call Group feature is enabled, the phone can receive incoming calls when DND is enabled.
Interoperability	VOIP-107055	5.3.0	The VVX series phone no longer causes any issues when monitoring BroadSoft BLF with long press when dialog terminates.
Localization	VOIP-107728	5.4.0	Japanese characters are now displayed correctly under the Calendar menu of the phone.

<i>Category</i>	<i>Issue No.</i>	<i>Release</i>	<i>Description</i>
Localization	VOIP-107316	5.4.0	Using German as language now displays correctly the Settings Menu as Einstellung.
Localization	VOIP-105148	5.4.0	The Recent Call list now displays the umlaute correctly while using LYNC Base Profile and Exchange on VVX 500 and 600 phones.
Lync	VOIP-108407	5.4.0	In the Idle Screen, Message Count will be shown incrementally upon receiving a Voice Mail on Lync-enabled phones.
Lync	VOIP-107953	5.4.0	In Microsoft Lync deployments, the phone now observes only one Microsoft subnet message and no longer causes any call issues.
Lync	VOIP-107795	5.4.0	VVX 5XX/6XX Utilizes newly added <code>device.lync.timeZone</code> Parameter works AN issue and does not show any errors in the log.
Lync	VOIP-106545 VOIP-106544 VOIP-105835	5.3.0	The Lync SLA feature now works during WAN outage with only SBS available.
Lync	VOIP-105932	5.3.1	In Lync Boss Admin scenario, direct Blind transfer to the Boss voicemail is now working.
Lync	VOIP-102580	5.2.0	A problem was resolved that caused issues when establishing a call with an Avaya IP phone in a Lync 2013 environment.
Power	VOIP-108815	5.4.0	Power usage values for VVX 101 and 201 have been changed from 5000mw to 3500mw to support some specific switches.
Registration	VOIP-108215	5.4.0	Following a software upgrade, both Pin and Extension from Flash/configuration parameters are now used to fetch the certificate enabling user registration.
Registration	VOIP-102393	4.1.8	Currently, Polycom phones send a REGISTER message with new call-ID for each re-registration once it is unregistered. If you enable this config parameter, the phone will not create a new call-ID for each re-registration until reboot. Refer to the Configuration File Enhancement section for details of this parameter.
Security	VOIP-103745	5.4.1	Resolved important security vulnerabilities.
Security	VOIP-102522	5.2.3	Resolved important security vulnerabilities.
SIP	VOIP-99638	4.1.8	A problem was resolved that caused phones to momentarily lose connection when SIP/TLS is in use.
User Interface	VOIP-106898	5.3.1	On the Off the hook mode phone now displays "Dial pad", "Contact" and "Recent" soft keys when "Feature.directory.enable" is disabled.
User Interface	VOIP-105634	5.3.1	The phone now displays the Parked call line and the Retrieve soft key for retrieving the paging as expected.

<i>Category</i>	<i>Issue No.</i>	<i>Release</i>	<i>Description</i>
User Interface	VOIP-103976	5.4.0	The phone now displays the email address or username for external non-Lync contacts added to Outlook.
User Interface	VOIP-103281	5.4.0	The Configuration Status menu display now truncates and displays the information properly even when the length of the server address is very long.
BToE	VOIP-106202	5.3.1	When BToE is activated and received calls from Response group, Phone now displays the name and number correctly.
Expansion Modules	VOIP-102708	5.4.0	Stability and performance have been improved for VVX Expansion Modules.
Bluetooth	VOIP-102614	5.4.0	Audio quality via Bluetooth on the receiver side has been improved

Get Help

For more information about installing, configuring, and administering Polycom products, refer to [Polycom Support](#).

For information about Polycom partner solutions, see [Polycom Global Strategic Partner Solutions](#).

The Polycom Community

The [Polycom Community](#) gives you access to the latest developer and support information. Participate in discussion forums to share ideas and solve problems with your colleagues. To register with the Polycom Community, create a Polycom online account. When logged in, you can access Polycom support personnel and participate in developer and support forums to find the latest information on hardware, software, and partner solutions topics.

Copyright and Trademark Information

Copyright© 2017, Polycom, Inc. All rights reserved. No part of this document may be reproduced, translated into another language or format, or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Polycom, Inc.

6001 America Center Drive
San Jose, CA 95002
USA

Trademarks Polycom®, the Polycom logo and the names and marks associated with Polycom products are trademarks and/or service marks of Polycom, Inc., and are registered and/or common law marks in the United States and various other countries.



All other trademarks are property of their respective owners. No portion hereof may be reproduced or transmitted in any form or by any means, for any purpose other than the recipient's personal use, without the express written permission of Polycom.

Disclaimer While Polycom uses reasonable efforts to include accurate and up-to-date information in this document, Polycom makes no warranties or representations as to its accuracy. Polycom assumes no liability or responsibility for any typographical or other errors or omissions in the content of this document.

Limitation of Liability Polycom and/or its respective suppliers make no representations about the suitability of the information contained in this document for any purpose. Information is provided "as is" without warranty of any kind and is subject to change without notice. The entire risk arising out of its use remains with the recipient. In no event shall Polycom and/or its respective suppliers be liable for any direct, consequential, incidental, special, punitive or other damages whatsoever (including without limitation, damages for loss of business profits, business interruption, or loss of business information), even if Polycom has been advised of the possibility of such damages.

End User License Agreement BY USING THIS PRODUCT, YOU ARE AGREEING TO THE TERMS OF THE END USER LICENSE AGREEMENT (EULA) AT: <http://documents.polycom.com/indexes/licenses>. IF YOU DO NOT AGREE TO THE TERMS OF THE EULA, DO NOT USE THE PRODUCT, AND YOU MAY RETURN IT IN THE ORIGINAL PACKAGING TO THE SELLER FROM WHOM YOU PURCHASED THE PRODUCT.

Patent Information The accompanying product may be protected by one or more U.S. and foreign patents and/or pending patent applications held by Polycom, Inc.

Open Source Software Used in this Product This product may contain open source software. You may receive the open source software from Polycom up to three (3) years after the distribution date of the applicable product or software at a charge not greater than the cost to Polycom of shipping or distributing the software to you. To receive software information, as well as the open source software code used in this product, contact Polycom by email at OpenSourceVideo@polycom.com.

Customer Feedback We are striving to improve our documentation quality and we appreciate your feedback. Email your opinions and comments to DocumentationFeedback@polycom.com.

Polycom Support Visit the [Polycom Support Center](#) for End User License Agreements, software downloads, product documents, product licenses, troubleshooting tips, service requests, and more.